

Placa de baza Asus PRIME A520M-K Socket LGA AM4



Pret: 332⁴⁷ RON (fara TVA)

Disponibilitate: Comanda speciala

Descriere

Placa de baza Asus PRIME A520M-K Socket LGA AM4 CPU Build in AMD AM4 Socket Processors * * Refer to www.asus.com for CPU support list Chipset AMD A520 Memory 2 x DIMM, Max. 64GB, DDR4 4600(O.C.)/4400(O.C.)/4000(O.C.)/3866(O.C.)/3733(O.C.)/3600(O.C.)/3466(O.C.)/3333(O.C.)/3200/3000/2800/2666/2400/2133 MHz Un-buffered Memory * Dual Channel Memory Architecture ECC Memory (ECC mode) support varies by CPU. * Refer to www.asus.com for the Memory QVL (Qualified Vendors Lists). * The maximum memory frequency supported varies by processor. Graphic 1 x D-Sub 1 x HDMI 2.1(4K@60HZ) Expansion Slots 3rd Gen AMD Ryzen™ and 3rd Gen AMD Ryzen™ with Radeon™ Graphics Processors 1 x PCIe 3.0 x16 (x16 mode) AMD A520 Chipset 2 x PCIe 3.0 x1 Storage Total supports 1 x M.2 slot(s) and 4 x SATA 6Gb/s ports 3rd Gen AMD Ryzen™ and 3rd Gen AMD Ryzen™ with Radeon™ Graphics Processors : 1 x M.2 Socket 3, with M Key, Type 2242/2260/2280 (PCIe 3.0 x4 and SATA modes) storage devices support AMD A520 Chipset : 4 x SATA 6Gb/s port(s), Support Raid 0, 1, 10 LAN Realtek RTL8111H 1Gb Ethernet ASUS LANGuard Audio Realtek ALC887 7.1 Surround Sound High Definition Audio CODEC * - Supports : Jack-detection, Multi-streaming, Front Panel Jack- retasking, up to 24-Bit/192kHz playback Audio Feature : - Audio Shielding - Dedicated audio PCB layers <https://www.asus.com/Motherboards/PRIME-A520M-K/specifications/>